WB-200 Series SECURITY HEADSETS



ALTAIR WAM-SEC

DESCRIPTION

-Headset designed for security personnel or discrete fitting applications. The earphone could be easily hidden under the ear.

-The earphone, made on transparent tubing material could be worn under helmets: sports or risk situations.

-Microphone is an electret type and incorporates dual function: **VOX** (always active) or **PTT** (push to Talk) key.

-Connector mini XLR4pin F. Cable length 2m. Weight 50 gr.

-Mic Electret omnidirectional. D C 9V .Impedance 2Kohm

-Earpiece. Acoustic tubing. Impedance 50 ohm.

RECOMMENDED CONFIGURATION

WBP-200/202

-Set the microphone input to electret type: Open the unit and place one jumper in the connector marked as J P-2 (PHANTOM). Jumper is close to headset connector.
-Adjust the microphone gain: Press and hold the MIC key, and with the Vol+/Vol- keys, adjust the level 3 points LOWER than the maximum setting.
-Adjust the side tone level (your own voice listening): Press and hold the BUZZ key and with the Vol+/Vol- keys, adjust the level 3 points LOWER than the maximum setting.

WBP-210/212

-Adjust the setting as above by the corresponding menu settings.

WBS-200/WBS-202

-Set the microphone input to electret type: Open the unit and place one jumper in the connector marked as J P-2 (PHANTOM). This jumper in on the bottom left corner of the pcb.
-Adjust the microphone gain: Open the unit and remove the jumper in the connector marked as JP1 (Gain) to Low. Same place as above