ZED 436



32 MIC/LINE INPUTS

2 DUAL STEREO INPUTS

4 SUB GROUPS

6 AUX SENDS

FEATURES

32 mono channels
2 dual stereo inputs with 4-band EQ
Neutrik mic XLR
Neutrik 1/4 inch jacks
Channel insert
Super wide gain mic/line input
4-band EQ with 2 swept mids and in/out switch
Illuminated mute
Sound image pan
Illuminated PFL & peak warning indicator
ALPS 100mm faders
6 auxiliary sends (2 pre, 2 post, 2 pre/post)
4 sub groups fed from each channel
All inputs with level control
12 bar meters
L, R and M main mix outputs
2 matrix sections available; can send output to USB
Individual channel 48V phantom power
Direct output on every mono channel
Peak and signal indication on every channel
Configurable USB stereo audio in/out
Master level controls on all outputs
Easy to use layout – all connections and controls on top surface



