

# Side-Address



## PGA27

CARDIOID | CONDENSER  
**Large Diaphragm  
 Side-Address Microphone**

Versatile sound from a large cardioid diaphragm with tailored frequency response and a high SPL threshold.




20Hz – 20kHz

## PGA181

CARDIOID | CONDENSER  
**Side-Address Microphone**

Extremely versatile microphone with smooth frequency response for vocals as well as acoustic and amplified instruments.



50Hz – 20kHz

## Studio Kit

Wide variety of flexible professional sound solutions that apply to most recording opportunities.

### PGASudioKit4

**Four-Piece  
 Microphone Kit**



- INCLUDES:**
- (3) Microphone Clips
  - (4) 15ft (4.57m) XLR-XLR Cables
  - Soft Zipper Carrying Case

## Drum Kits

Essential package of professional quality microphones for a wide variety of drum and percussion applications.

### PGADrumKit5

**Five-Piece  
 Microphone Kit**



- INCLUDES:**
- Microphone Clip
  - (3) Drum Mounts
  - (5) 15ft (4.57m) XLR-XLR Cables
  - Soft Zipper Carrying Case

### PGADrumKit7

**Seven-Piece  
 Microphone Kit**



- INCLUDES:**
- (3) Microphone Clips
  - (3) Drum Mounts
  - (7) 15ft (4.57m) XLR-XLR Cables
  - Soft Zipper Carrying Case

## SPECIFICATIONS

| Model         | Type      | Frequency Response | Polar Pattern | Sensitivity (at 1 kHz)                         | Output Impedance | Maximum SPL (at 1% kHz)                   | Net Weight           |
|---------------|-----------|--------------------|---------------|--|------------------|---|----------------------|
| <b>PGA27</b>  | Condenser | 20 to 20,000 Hz    | Cardioid      | Open Circuit Voltage<br>-35 dBV/Pa (17.8 mV)   | 115 Ω            | 130 dB SPL Pad Off<br>(145 dB SPL Pad On) | 453 grams (16.0 oz)  |
| <b>PGA48</b>  | Dynamic   | 70 to 15,000 Hz    | Cardioid      | Open Circuit Voltage<br>-53.5 dBV/Pa (2.10 mV) | 600 Ω            | NA  | 300 grams (10.58 oz) |
| <b>PGA52</b>  | Dynamic   | 50 to 12,000 Hz    | Cardioid      | Open Circuit Voltage<br>-55 dBV/Pa (1.75 mV)   | 150 Ω            | NA  | 454 grams (16.01 oz) |
| <b>PGA56</b>  | Dynamic   | 50 to 15,000 Hz    | Cardioid      | Open Circuit Voltage<br>-57 dBV/Pa (1.45 mV)   | 200 Ω            | NA  | 287 grams (10.12 oz) |
| <b>PGA57</b>  | Dynamic   | 50 to 15,000 Hz    | Cardioid      | Open Circuit Voltage<br>-56.5 dBV/Pa (1.5 mV)  | 150 Ω            | NA  | 280 grams (9.88 oz)  |
| <b>PGA58</b>  | Dynamic   | 50 to 16,000 Hz    | Cardioid      | Open Circuit Voltage<br>-55 dBV/Pa (1.79 mV)   | 150 Ω            | NA  | 294 grams (10.37 oz) |
| <b>PGA81</b>  | Condenser | 40 to 18,000 Hz    | Cardioid      | Open Circuit Voltage<br>-48.5 dBV/Pa (3.8 mV)  | 600 Ω            | 129.5 dB SPL                              | 186 grams (6.56 oz)  |
| <b>PGA98D</b> | Condenser | 60 to 20,000 Hz    | Cardioid      | Open Circuit Voltage<br>-52 dBV/Pa (2.51 mV)   | 850 Ω            | 130 dB SPL                                | 210 grams (7.41 oz)  |
| <b>PGA98H</b> | Condenser | 60 to 20,000 Hz    | Cardioid      | Open Circuit Voltage<br>-52 dBV/Pa (2.51 mV)   | 850 Ω            | 130 dB SPL                                | 210 grams (7.41 oz)  |
| <b>PGA181</b> | Condenser | 50 to 20,000 Hz    | Cardioid      | Open Circuit Voltage<br>-38 dBV/Pa (12.7 mV)   | 120 Ω            | 138 dB SPL                                | 383 grams (13.51 oz) |

All specifications subject to change

**SHURE**<sup>®</sup>  
LEGENDARY  
PERFORMANCE™

**United States, Canada,  
Latin America, Caribbean:**  
Shure Incorporated  
5800 West Touhy Avenue  
Niles, IL 60714-4608 USA

Phone: 847-600-2000  
Fax: 847-600-1212 (USA)  
Fax: 847-600-6446  
Email: info@shure.com

**Europe, Middle East, Africa:**  
Shure Europe GmbH  
Jakob-Dieffenbacher-Str. 12,  
75031 Eppingen, Germany

Phone: 49-7262-92490  
Fax: 49-7262-9249114  
Email: info@shure.de

**Asia, Pacific:**  
Shure Asia Limited  
22/F, 625 King's Road  
North Point, Island East  
Hong Kong

Phone: 852-2893-4290  
Fax: 852-2893-4055  
Email: info@shure.com.hk